

M A T R O X  
G E N E S I S

**April 9, 1999**

**XILLIX PMI 1400**

**Matrox Genesis (GEN-STD)**

VIDEO  
LINE ENA.  
FRAME ENA.  
PIX STROBE  
EXPOSE

# Application Note:

## Interfacing non-standard cameras to Matrox Genesis

Xillix PMI 1400

April 9, 1999

<b>Cabling Requirements</b>	<b>Mode: Control (high resolution mode-software reset)</b>			
	<ul style="list-style-type: none"> <li>DBHD100-TO-OPEN cable and GEN/DIG/BRD/R board required for digital data, synchronization and control signals in RS-422 format.</li> <li>Connections between the 50-pin connector of the camera and the 100-pin connector of the GEN-DIG-BRD/R are as follows:</li> </ul>			
	<b>XILLIX PMI 1400</b>		<b>GEN-DIG-BRD/R</b>	
	<b>(50-pin connector)</b>		<b>(100-pin connector)</b>	
	<b>Pin name</b>	<b>Pin no.</b>	<b>Pin name</b>	<b>Pin no.</b>
	EXPOSE +	02	← EXPOSURE1, OUTPUT, +	95
	EXPOSE -	27	← EXPOSURE1, OUTPUT, -	96
	PIXEL STROBE +	04	→ CLOCK, INPUT, +	39
	PIXEL STROBE -	29	→ CLOCK, INPUT, -	40
	FRAME ENABLE +	06	→ VSYNC, INPUT, +	35
	FRAME ENABLE -	31	→ VSYNC, INPUT, -	36
	LINE ENABLE +	07	→ HSYNC, INPUT, +	33
	LINE ENABLE -	32	→ HSYNC, INPUT, -	34
	GND	08	→ GROUND	37
	GND	33	→ GROUND	38
	MODE CONTROL 3 +	09	← USER, OUTPUT, 0 +	91
	MODE CONTROL 3 -	34	← USER, OUTPUT, 0 -	92
	MODE CONTROL 1 +	11	← USER, OUTPUT, 1 +	93
	MODE CONTROL 1 -	36	← USER, OUTPUT, 1 -	94
	DATA 12 (MSB) +	13	→ DATA, INPUT, 11+	23
	DATA 12 -	38	→ DATA, INPUT, 11-	24
	DATA 11 +	14	→ DATA, INPUT, 10+	21
	DATA 11 -	39	→ DATA, INPUT, 10-	22
	DATA 10 +	15	→ DATA, INPUT, 9+	19
	DATA 10 -	40	→ DATA, INPUT, 9-	20
	DATA 9 +	16	→ DATA, INPUT, 8+	17
	DATA 9 -	41	→ DATA, INPUT, 8-	18
	DATA 8 +	17	→ DATA, INPUT, 7+	15
	DATA 8 -	42	→ DATA, INPUT, 7-	16
	DATA 7 +	18	→ DATA, INPUT, 6+	13
	DATA 7 -	43	→ DATA, INPUT, 6-	14
	DATA 6 +	19	→ DATA, INPUT, 5+	11
	DATA 6 -	44	→ DATA, INPUT, 5-	12
	DATA 5 +	20	→ DATA, INPUT, 4+	09
	DATA 5 -	45	→ DATA, INPUT, 4-	10
	continued			

# Application Note:

## Interfacing non-standard cameras to Matrox Genesis

Xillix PMI 1400

April 9, 1999

Cabling Requirements (cont.)	XILLIX PMI 1400 (50-pin connector)		GEN-DIG-BRD/R (100-pin connector)	
	Pin name	Pin no.	Pin name	Pin no.
	DATA 4 +	21 →	DATA, INPUT, 3+	07
	DATA 4 -	46 →	DATA, INPUT, 3-	08
	DATA 3 +	22 →	DATA, INPUT, 2+	05
	DATA 3 -	47 →	DATA, INPUT, 2-	06
	DATA 2 +	23 →	DATA, INPUT, 1+	03
	DATA 2 -	48 →	DATA, INPUT, 1-	04
	DATA 1 (LSB) +	24 →	DATA, INPUT, 0+	01
	DATA 1 (LSB) -	49 →	DATA, INPUT, 0-	02
	GND	25 →	GROUND	37

The DCF(s) mentioned in this application note can be found on the MIL and Native Library CD, or our FTP site ([ftp.matrox.com](ftp:matrox.com)). The information furnished by Matrox Electronics System, Ltd. is believed to be accurate and reliable. Please verify all interface connections with camera documentation or manual. Contact your local sales representative or Matrox Sales office or Matrox Imaging Applications at 514-822-6061 for assistance.

**Corporate Headquarters:**  
**Canada and U.S.A.**  
**Matrox Electronic Systems Ltd.**  
 1055 St.Regis Blvd.  
 Dorval, Quebec, Canada  
 H9P 2T4  
 Tel: (514) 685-7230  
 Fax: (514) 822-6273

**Sales Offices:**  
**U.K.**  
**Matrox (UK) Ltd.**  
 Sefton Park, Stoke Poges  
 Buckinghamshire  
 U.K. SL2 4JS  
 Tel: +44 (0) 1753 665500  
 Fax: +44 (0) 1753 665599

**France**  
**Matrox France SARL**  
 2, rue de la Couture,  
 Silic 225  
 94528 Rungis Cedex  
 Tel: (0) 1 45-60-62-00  
 Fax: (0) 1 45-60-62-05

**Germany**  
**Matrox GmbH**  
 Inselkammerstr.8  
 D-82008  
 Unterhaching  
 Germany  
 Tel: 089/614 4740  
 Fax: 089/614 9743

**Asia Pacific**  
**Matrox Asia Liaison Office**  
 Rm. 1901, 19/F, Workington  
 Tower,  
 78 Bonham Strand E.,  
 Sheung Wan, Hong Kong.  
 Tel: 852.2877.5387  
 Fax: 852.2537.9530

